

Transformers, Power Supplies 30W, 60W, 150W

CE ROHS IP67

			
Model	MTXout-30w	MTXout-60w	MTXout-150w
Item Identifier	ET7-99-1	ET7-100-1-1	ET7-101-1-1
Discription	30W Transformer Power Supply	60W Transformer Power Supply	150W Transformer Power Supply
Output voltage	12V±4%		
Output Current	2.5A	5A	12.5A
Ripple and noise	220mVp-p	220mVp-p	220mVp-p
Output power	30W	60W	150W
Efficiency	0.88	0.87	0.86
Input voltage	100-250VAC		
Input frequency	47-63Hz		
Input current	2A/110V 1A/220V		3A/110V 1.5A/220V
Cold start current	3.3A/170V 2A/260V	3A/170V 1.7A/260V	5A/170V 3A/260V
Leakage current	<0.5mA/260VAC		
Waterproof grade	IP67		
Overload protection	105%-110%,cut off the output, reset: automatic recovery		
Short circuit protection.	Have		
Over voltage protection	Have		
Temp coefficient	±0.03%°C(0-5°C)		
Start, rise, hold time	200ms,50ms,20ms		
Shock resistance	10-500Hz,2G 10min,/1 cycle, 60 minutes, each axis		
Pressure	I/P-O/P:3.0KVAC,I/P-FG 1.5KVAC,O/P-FG:0.5KVAC		
Running Temp, humidity	-20°C~+60°C , 20%~90%RH		
Storage Temp , humidity	-30°C~+85°C , 10%~95%RH		
Dimension	220*30*20mm	168*52*34mm	240*69*43mm
Weight	0.3Kg	0.6Kg	1.2Kg
Security Standard	CE FCC ROHS		

Transformers Power Supplies 30W, 60W, 150W

CE ROHS IP67